

# Growatt ShineLink-X

- Cable free, easy installation
- Dynamic IP, plug and play
- Communication distance up to 120m
- Support up to 3 devices
- Built-in memory for up to one month of data
- Online monitoring and maintenance



P O W E R  
- I N G O  
T O M O -  
R R O W O

**GROWATT**

[www.ginverter.com](http://www.ginverter.com)

| Datasheet                         | ShineLink-X            |
|-----------------------------------|------------------------|
| <b>Communication Interface</b>    |                        |
| RF433                             | Yes                    |
| RF433(No barrier wall)            | Up to 120 m            |
| RF433(two walls blocking)         | 20 m                   |
| <b>Power Supply</b>               |                        |
| Power consumption                 | <2W standby, <5W peak  |
| Voltage range                     | 196V~250V              |
| Frequency                         | 50/60Hz                |
| <b>General Specifications</b>     |                        |
| Dimensions(L/W/H)                 | 105/85/26mm            |
| Weight                            | < 1kg                  |
| Mounting options                  | Tabletop/wall-mount    |
| Protection degree                 | IP30                   |
| Display                           | LED                    |
| Ambient temperature range         | -20 to 65 °C           |
| Humidity                          | 0-95% (non condensing) |
| <b>Features</b>                   |                        |
| Remote firmware upgrade           | Yes                    |
| Max. number of devices to monitor | 3(RF433)               |
| CE                                |                        |